

**Band Pass Filter [CDMA Reject]**  
[Model No: VR-BF-922-D75]

*Vedang* Band Pass Filter is high performance equipment used to reduce the interference of CDMA transmit frequency in EGSM / GSM 900 band caused due to close proximity of CDMA and GSM sites. These Filters are characterized by:

- Low Insertion Loss
- High Rejection at critical spots through customized design
- Excellent return loss

**Specifications:**

Pass Band Frequency	885 – 960 MHz
Pass Band Insertion Loss	
885 MHz	0.90 dB (Typical)
887 MHz	0.70 dB (Typical)
925-960 MHz	0.45 dB (Typical)
Rejection	
878 MHz	45 dB
< 877 MHz	50 dB
Return Loss	20 dB (Min)
Impedance	50 Ω
Operating Temperature	-10° C – +55° C
Connector Type	DIN (F)
Environment	Indoor
Weight	2.1 Kg (Appx.)
Dimensions	177 x 73 x 73.5 mm (Appx.)