

Band Pass Filter [CDMA Reject]
[Model No: VR-BF-925-C70]

Vedang Band Pass Filter is high performance equipment used to reduce the interference of CDMA transmit frequency in EGSM / GSM 900 band caused due to close proximity of CDMA and GSM sites. These Filters are characterized by:

- Low Insertion Loss
- High Rejection at critical spots through customized design
- Excellent return loss

Specifications:

Pass Band Frequency	890 – 960 MHz
Pass Band Insertion Loss	
890 MHz	1.95 dB (Typical)
892 MHz	0.90 dB (Typical)
894-960 MHz	0.60 dB (Typical)
Rejection	
887 MHz	35 dB
< 885 MHz	50 dB
Return Loss	20 dB (Min)
Impedance	50 Ω
Operating Temperature	-10° C – +55° C
Connector Type	DIN (F)
Environment	Indoor
Weight	2.1 Kg (Appx.)
Dimensions	177 x 73 x 73 mm (Appx.)