



## GSM Full Band Repeater –Dual Band

(Model No: AVR 10 C MG)

### Specifications:

Power Output	:	+ 10 dBm
Band Width	:	As per ETSI Specification
Downlink Gain	:	50 dB
Uplink Gain	:	Dynamic and varies as per customer's proximity to receive antenna (of repeater)
Gain Adjustment	:	3 dB steps
Noise Figure	:	6dB (Typ)
Group Delay	:	< 3.8 $\mu$ Sec
In/Out Impedance	:	50 ohms
Return Loss	:	> 10 dB
RF Connectors	:	N - Female
Supply Voltage	:	90-260 V Ac, 50 $\pm$ 3 Hz
Operating temperature	:	0 $^{\circ}$ to +55 $^{\circ}$ C
Weather Proof	:	IP55

---

#### Manufactured By :

##### **Avantel Softech Limited**

Plot No. 16, Sector-III, HUDA Techno Enclave,  
Madhapur, Hyderabad - 500 081, India.  
Tel : +91-40-2550 4056/57/58 Fax : +91-40-2311 2336  
E-mail: [marketing@avantelsoftech.com](mailto:marketing@avantelsoftech.com)  
[www.avantelsoftech.com](http://www.avantelsoftech.com)

#### Marketed By :

##### **Vedang Radio Technology Pvt Ltd**

105,Nirman Industrial Estate Link Road, Malad (West),  
Mumbai-400064, Maharashtra, India  
Phone:(22)-28788001 Fax:(22)-28788002  
E-mail: [sales@vedangradio.com](mailto:sales@vedangradio.com)  
[www.vedangradio.com](http://www.vedangradio.com)